


NAIS

FLAT/VERTICAL TYPE HIGH POWER BIFURCATED CONTACT


NC-RELAYS

UL File No.: E43028; CSA File No.: LR26550



Flat series

	a
2C	25.4 1.000
4C	38.1 1.500



Vertical series (PC board)

NCED
Amber Relays
mm inch

	a
2C	25.4 1.000
4C	38.1 1.500

- Space saver - Flat series and vertical series
- High contact reliability due to bifurcated contacts — 2C: 5 A 250 V AC, 4C: 5 A 125 V AC, 4 A 250 V AC
- Latching types available
- Low operating power — 2C: 200 mW, 4C: 400 mW (Single side stable)
- Soldering flux inflow prevented by terminal location
- Amber sealed types available
- High breakdown voltage for transient protection — 1,000 Vrms between open contacts, contact sets

SPECIFICATIONS

Contacts

Types	Standard	Amber sealed
Arrangement	2 Form C, 4 Form C	
Initial contact resistance, max. (By voltage drop 6 V DC 1 A)	50 mΩ	
Rating (resistive load)	Max. switching power	(2C) 1,250 VA (4C) 1,000 VA
	Max. switching voltage	250 V AC
	Max. switching current	5 A
	Max. switching carrying current	5 A
	Min. switching power	100 μA 1 V DC
	UL/CSA rating	(2C) 5 A 125, 250 V AC (4C) 5 A 125 V, 4 A 250 V AC 1/10 HP 125, 250 V AC 5 A 30 V DC
VDE rating	3 A 125 V AC (cosφ = 1.0) 0.5 A 125 V AC (cosφ = 0.4) 3 A 30 V DC	1 A 125 V AC (cosφ = 1.0) 0.5 A 125 V AC (cosφ = 0.4) 1 A 30 V DC
Expected life (minimum)	2C	10 ⁶ at 5 A 250 V AC 5×10 ⁵ at 5 A 30 V DC
	4C	10 ⁶ at 4 A 250 V AC 10 ⁶ at 5 A 125 V AC 5×10 ⁵ at 5 A 30 V DC
Contact material	Gold-clad silver nickel	

Coil (Polarized) (at 25°C 77°F)

Minimum operating power	Up to 48 V DC		110 V DC
	2 C single side stable	Approx. 200 mW	500 mW
4 C single side stable	Approx. 400 mW	500 mW	
Nominal operating power	2 C single side stable	Approx. 360 mW	900 mW
	4 C single side stable	Approx. 720 mW	900 mW
Minimum set and reset power	2 C 2 coil latching	Approx. 450 mW	
	4 C 2 coil latching	Approx. 900 mW	
Nominal set and reset power	2 C 2 coil latching	Approx. 800 mW	
	4 C 2 coil latching	Approx. 1,600 mW	

Remarks

- *1 Detection current: 10 mA
- *2 Half-wave pulse of sine wave: 11ms; detection time: 10μs
- *3 Half-wave pulse of sine wave: 6ms
- *4 Detection time: 10μs
- *5 Refer to 5. Conditions for operation, transport and storage mentioned in AMBIENT ENVIRONMENT (Page 49)

Characteristics (at 25°C 77°F 50% Relative humidity)


Max. operating speed	50 cps.		
Initial insulation resistance	Min. 100 MΩ at 500 V DC		
Initial breakdown voltage*1	Between open contacts, contact sets	1,000 Vrms	
	Between contacts and coil	2,000 Vrms	
Operate time (at nominal voltage)	Approx. 10 ms		
Release time (at nominal voltage)	Approx. 5 ms		
Operate time (latching) (at nominal voltage)	Approx. 10 ms		
Reset time (latching) (at nominal voltage)	Approx. 5 ms		
Temperature rise (at nominal voltage)	Max. 65°C		
Shock resistance	Functional*2	Min. 98 m/s ² {10 G}	
	Destructive*3	Min. 980 m/s ² {100 G}	
Vibration resistance	Functional*4	58.8 m/s ² {6 G}, 10 to 55 Hz at double amplitude of 1 mm	
	Destructive	117.6 m/s ² {12 G}, 10 to 55 Hz at double amplitude of 2 mm	
Conditions for operation, transport and storage*5 (Not freezing and condensing at low temperature)	(Single side stable)	2 C	up to 48 V DC: -40°C to +70°C -40°F to +158°F 110 V DC: -40°C to +55°C -40°F to +131°F
		4 C	-40°C to +55°C -40°F to +131°F
	(2 coil latching)		-40°C to +55°C -40°F to +131°F
Humidity	5 to 85% R.H.		
Unit weight	2C/Approx. 16 g .56 oz 4C/Approx. 18 g .63 oz		

TYPICAL APPLICATIONS

Use NC Relays for power control up to 5 A or —

Where equipment size limits relay mounting space		Tape recorders, temperature controls, video tape recorders
Where transistor drive demands high sensitivity, low power		Telecommunications equipment, measuring controls, copiers
Where relays must be mounted on P/C boards at minimum cost and labor		Date processing equipment, computer peripherals
Where low-capacity power requires low power dissipation		Automatic vendors, copiers, automatic storage controls, N.C. machines

ORDERING INFORMATION



Contact arrangement	Type classification	Housing	Mounting method	Operating function	Coil voltage
2: 2 Form C 4: 4 Form C	Nil: Standard type E: Amber sealed type	Nil: Vertical series J: Flat series	Nil: Plug-in P: PC board terminal	Nil: Single side stable L2: 2 coil latching	DC 5, 6, 12, 24, 48, 110 V

- (Notes) 1. Flat series are available in PC board terminal types only.
 2. For VDE recognized type, add suffix VDE.
 3. Standard packing Carton: 20 pcs. Case: 200 pcs.

TYPE AND COIL DATA at 20°C 68°F (Coil data for Amber sealed types are same as those for standard types.)

2 Form C Single side stable

Flat series	Vertical series		Coil voltage, V DC			Coil resistance, Ω (±10%)	Nominal operating power, mW
	PC board terminal	Plug-in	PC board terminal	Pick-up voltage (max.)	Drop-out voltage (min.)		
NC2D-JP-DC5V	NC2D-DC5V	NC2D-P-DC5V	4.0	0.5	6.75	69.4	360
NC2D-JP-DC6V	NC2D-DC6V	NC2D-P-DC6V	4.8	0.6	8.1	100	
NC2D-JP-DC12V	NC2D-DC12V	NC2D-P-DC12V	9.6	1.2	16.2	400	
NC2D-JP-DC24V	NC2D-DC24V	NC2D-P-DC24V	19.2	2.4	32.4	1,600	
NC2D-JP-DC48V	NC2D-DC48V	NC2D-P-DC48V	38.4	4.8	64.8	6,400	
NC2D-JP-DC110V	NC2D-DC110V	NC2D-P-DC110V	88.0	11.0	121	13,500	900

2 Form C 2 coil latching

Flat series	Vertical series		Coil voltage, V DC			Coil resistance, Ω (±10%)	Nominal operating power, mW
	PC board terminal	Plug-in	PC board terminal	Pick-up voltage (max.)	Reset voltage (max.)		
NC2D-JPL2-DC5V	NC2D-L2-DC5V	NC2D-PL2-DC5V	4.0	4.0	5.5	31.3	800
NC2D-JPL2-DC6V	NC2D-L2-DC6V	NC2D-PL2-DC6V	4.8	4.8	6.6	45.0	
NC2D-JPL2-DC12V	NC2D-L2-DC12V	NC2D-PL2-DC12V	9.6	9.6	13.2	180	
NC2D-JPL2-DC24V	NC2D-L2-DC24V	NC2D-PL2-DC24V	19.2	19.2	26.4	720	
NC2D-JPL2-DC48V	NC2D-L2-DC48V	NC2D-PL2-DC48V	38.4	38.4	52.8	2,880	
NC2D-JPL2-DC110V	NC2D-L2-DC110V	NC2D-PL2-DC110V	88.0	88.0	121	15,100	

4 Form C Single side stable

Flat series	Vertical series		Coil voltage, V DC			Coil resistance, Ω (±10%)	Nominal operating power, mW
	PC board terminal	Plug-in	PC board terminal	Pick-up voltage (max.)	Drop-out voltage (min.)		
NC4D-JP-DC5V	NC4D-DC5V	NC4D-P-DC5V	4.0	0.5	5.5	34.7	720
NC4D-JP-DC6V	NC4D-DC6V	NC4D-P-DC6V	4.8	0.6	6.6	50	
NC4D-JP-DC12V	NC4D-DC12V	NC4D-P-DC12V	9.6	1.2	13.2	200	
NC4D-JP-DC24V	NC4D-DC24V	NC4D-P-DC24V	19.2	2.4	26.4	800	
NC4D-JP-DC48V	NC4D-DC48V	NC4D-P-DC48V	38.4	4.8	52.8	3,200	
NC4D-JP-DC110V	NC4D-DC110V	NC4D-P-DC110V	88.0	11.0	121	13,500	900

4 Form C 2 coil latching

Flat series	Vertical series		Coil voltage, V DC (See Note 1)			Coil resistance, Ω (±10%)	Nominal operating power, mW
	PC board terminal	Plug-in	PC board terminal	Pick-up voltage (max.)	Reset voltage (max.)		
NC4D-JPL2-DC5V	NC4D-L2-DC5V	NC4D-PL2-DC5V	4.0	4.0	5.5	15.6	1,600
NC4D-JPL2-DC6V	NC4D-L2-DC6V	NC4D-PL2-DC6V	4.8	4.8	6.6	22.5	
NC4D-JPL2-DC12V	NC4D-L2-DC12V	NC4D-PL2-DC12V	9.6	9.6	13.2	90	
NC4D-JPL2-DC24V	NC4D-L2-DC24V	NC4D-PL2-DC24V	19.2	19.2	26.4	360	
NC4D-JPL2-DC48V	NC4D-L2-DC48V	NC4D-PL2-DC48V	38.4	38.4	52.8	1,440	
NC4D-JPL2-DC110V	NC4D-L2-DC110V	NC4D-PL2-DC110V	88.0	88.0	121	7,560	

Notes:

- Two coil latching relay 4C series are for intermittent operation only. Power should be applied to coil continuously for no more than two minutes.
- Coil resistance is the measured value at a coil temperature of 20°C. Compensate coil resistance by plus or minus 0.4% for each degree (°C) of coil temperature change.
- "Maximum allowable voltage" is that value at maximum contact rating and maximum ambient temperature. The graph shown in the data describes the inter-relationship; care should be taken to prevent the total of ambient temperature and the coil temperature rise from exceeding 120°C.

DIMENSIONS

Flat series


mm inch

Dimensions
General tolerance: $\pm 0.5 \pm 0.20$


Schematic
(Top view)

PC board pattern
(Copper-side view)
Tolerance: $\pm 0.1 \pm 0.004$


2C single side stable (NC2D-JP)




2C 2 coil latching (NC2D-JPL2)



4C single side stable (NC4D-JP)



4C 2 coil latching (NC4D-JPL2)








Slim series

PC board series	Dimensions		Schematic (Bottom view)	PC board pattern (Copper-side view)
	General tolerance: $\pm 0.5 \pm .020$	Standard type		


**2C single side stable
(NC2D-P)**



(NC2ED-PL2)



Deenergized position



**2C 2 coil latching
(NC2D-PL2)**



(NC2ED-P)















Diagram shows the "reset" position when terminals 3 and 6 are energized. Energize terminals 4 and 5 to transfer contacts.




**4C single side stable
(NC4D-P)**




(NC4ED-P)



Deenergized position



**4C 2 coil latching
(NC4D-PL2)**



(NC4ED-PL2)









Diagram shows the "reset" position when terminals 3 and 6 are energized. Energize terminals 4 and 5 to transfer contacts.



Slim series

Dimensions

Plug-in series General tolerance: $\pm 0.5 \pm 0.20$

Standard type






Amber sealed type

Schematic
(Bottom view)

2C single side stable (NC2D)



(NC2ED)



Deenergized position

2C 2 coil latching (NC2D-L2)



(NC2ED-L2)














Diagram shows the "reset" position when terminals 3 and 6 are energized. Energize terminals 4 and 5 to transfer contacts.

4C single side stable (NC4D)




(NC4ED-L2)



Deenergized position

4C 2 coil latching (NC4D-L2)



(NC4ED-L2)









Diagram shows the "reset" position when terminals 3 and 6 are energized. Energize terminals 4 and 5 to transfer contacts.



SCHEMATIC

— Energize relays only in the polarities shown —

1. Single side stable

Same operation as conventional magnetic relays.


Contacts will transfer only when coil is energized under indicated polarity.



2. 2 coil latching

Contacts will transfer only when coil is energized under indicated polarity.

Once transferred, contacts remain in that position even with power off until opposite coil is energized at indicated polarity.



Diagrams show the “set” position when terminals 4 (–) and 5 (+) are energized. When the coil current is


switched off, these contacts remain in “make” position. Energize terminals 3 (–) and 6 (+) to transfer the contacts.

Diagrams show the “reset” position when terminals 3 (–) and 6 (+) are energized. Energize terminals 4 (–) and


5 (+) to transfer the contacts.

REFERENCE DATA


1.-(1) Life curve
DC load (2C, 4C)




AC load (2C)




AC load (4C)




2.-(1) Temperature rise characteristics for single side stable
Measured portion: Inside the coil




2.-(2) Temperature rise characteristics for 2 coil latching
Measured portion: Inside the coil



3. Operate time for single side stable







4. Release time for single side stable







5.-(1) Rate of change in pick-up/drop-out voltage against distance when closely arranged

Samples: NC2D-P-DC24V (2c slim single side stable) 3 pcs. each for Nos. (1), (2) and (3)
Condition: Rated voltage is applied to both Nos. (1) and (3) relays, and pick-up/drop-out voltage of No. 2 2C type mounting (1)





5.-(2) Rate of change in pick-up/drop-out voltage against distance when closely arranged

Samples: NC4D-P-DC24V (4c slim single side stable) 3 pcs. each for Nos. (1), (2) and (3)
Condition: Rated voltage is applied to both Nos. (1) and (3) relays, and the pick-up/drop-out voltage of 4C type mounting (1)




6. Rate of change of pick-up and drop-out voltage




NC


7.-(1) Ambient temperature vs
Max. continuous voltage
Sample: NC2D-P-DC24 V (2c slim single side stable)



7.-(2) Ambient temperature vs
Max. continuous voltage
Sample: NC2D-P-DC110 V (2c slim single side stable), NC4D-P-DC24 V (4c slim single side stable)



ACCESSORIES



Sockets incorporate a spring clip at each end permitting single "snap-in"

attachment to chassis or panels - no screws necessary. Relays are held firmly

in the socket by clips integrally molded into the socket.

TYPES

For Flat series		
Part No.	Terminals	Mating relay
NC2-JPS	P/C board	NC2D-JP
NC4-JPS	P/C board	NC4D-JP
NC2-JPL2S	P/C board	NC2D-JPL2
NC4-JPL2S	P/C board	NC4D-JPL2

Standard packing:
Carton: 20 pieces
Case: 200 pieces

For Slim series		
Part No.	Terminals	Mating relay
NC2-PS	P/C board	NC2D-P
NC4-PS	P/C board	NC4D-P
NC2-SS	Solder	NC2D
NC4-SS	Solder	NC2D
NC2-L2PS	P/C board	NC4D-PL2
NC4-L2PS	P/C board	NC2D-PL2
NC4-L2SS	Solder	NC2D-L2
NC4-L2SS	Solder	NC4D-L2

SPECIFICATIONS

Maximum continuous current	Flat series: 5 A 250 V AC Slim series: 5 A 250 V AC
Initial breakdown voltage	2,000 V AC (Except for coil-coil of L2 types: 1,500 V AC)
Initial insulation resistance	100 MΩ at 500 V DC
Heat resistance	150°C (302°F) for one hour


Caution: Do not insert or remove relays while in the energized condition.

DIMENSIONS


Flat series

General tolerance: $\pm 0.5 \pm .020$

NC2-JPS
NC2-JPL2S




NC4-JPS
NC4-JPL2S




Slim series


NC2-SS
NC2-L2S




NC2-PS
NC2-L2P



NC4-SS
NC4-L2S




NC4-PS
NC4-L2P



NOTES


1. To maintain insulation between coils of 2 coil latching series, terminals 5 and 6 for flat series, and terminals 3 and 4 for slim series should be connected to provide common return.




2. 2 coil latching series 4C are for intermittent operation only. Power should be applied to coils continuously for no more than two minutes.

3. When designing printed circuit board patterns, note that:


(1) "Top View" wiring diagram is indicated for the Flat series because terminals can be seen from above.



(2) "Bottom View" wiring diagram is indicated for the Slim series because terminals can not be seen from above.



4. When using slim series in close proximity, mount all relays facing the same direction. Different mounting directions may cause change in the relay characteristics because NC relays are polarized.



5. Sockets

(1) When PC board series are used with socket, do not apply loads exceeding 3 A.

(2) Soldering should be done quickly to avoid damaging the thermoplastic body.

(3) Insulation will be optimum when wire connections are soldered as shown with all slim sockets.

