## **SIEMENS**

## **Data sheet**

## 6ES7134-6HD01-0BA1



SIMATIC ET 200SP, ANALOG INPUT MODULE, AI 4XU/I 2-WIRE STANDARD, PACKING UNIT: 1 PIECE, FITS TO BU-TYPE A0, A1, COLOR CODE CC03, MODULE DIAGNOSIS, 16BIT, +/-0,3%

General information	
Product type designation	Al 4x U/I 2-wire
HW functional status	From FS02
Firmware version	
<ul> <li>FW update possible</li> </ul>	Yes
usable BaseUnits	BU type A0, A1
Color code for module-specific color identification plate	CC03
Product function	
<ul> <li>I&amp;M data</li> </ul>	Yes; I&M0 to I&M3
<ul> <li>Isochronous mode</li> </ul>	No
<ul> <li>Measuring range scalable</li> </ul>	No
Engineering with	
<ul> <li>STEP 7 TIA Portal configurable/integrated from version</li> </ul>	V14 / -
<ul> <li>STEP 7 configurable/integrated from version</li> </ul>	V5.6 and higher
<ul> <li>PCS 7 configurable/integrated from version</li> </ul>	V8.1 SP1
<ul> <li>PROFIBUS from GSD version/GSD revision</li> </ul>	One GSD file each, Revision 3 and 5 and higher
<ul> <li>PROFINET from GSD version/GSD revision</li> </ul>	GSDML V2.3
Operating mode	
<ul> <li>Oversampling</li> </ul>	No
• MSI	No
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
nput current	
Current consumption, max.	37 mA; without sensor supply
Encoder supply	
24 V encoder supply	
• 24 V	Yes
Short-circuit protection	Yes
<ul> <li>Output current, max.</li> </ul>	20 mA; max. 50 mA per channel for a duration < 10 s
Power loss	
Power loss, typ.	0.85 W; Without encoder supply voltage
Address area	

	8 byte; + 1 byte for QI information
Address space per module, max.  Hardware configuration	5 5) to, 1 byte for Qrimorniation
Automatic encoding	Yes
Mechanical coding element	Yes
Type of mechanical coding element	Type A
Selection of BaseUnit for connection variants	Type A
2-wire connection	BU type A0, A1
Analog inputs	20 (300 / 10, / 11
	4: Differential inpute
Number of analog inputs permissible input voltage for voltage input (destruction	4; Differential inputs 30 V
limit), max.	30 V
permissible input current for current input (destruction	50 mA
limit), max.	
Cycle time (all channels), min.	Sum of the basic conversion times and additional processing times
	(depending on the parameterization of the active channels)
Input ranges (rated values), voltages	
• 0 to +10 V	Yes; 15 bit
— Input resistance (0 to 10 V)	120 kΩ
• 1 V to 5 V	Yes; 15 bit
— Input resistance (1 V to 5 V)	120 kΩ
• -10 V to +10 V	Yes; 16 bit incl. sign
— Input resistance (-10 V to +10 V)	120 kΩ
• -5 V to +5 V	Yes; 16 bit incl. sign 120 k $\Omega$
— Input resistance (-5 V to +5 V)	120 KΩ
Input ranges (rated values), currents	Voc. 15 hit
• 0 to 20 mA	Yes; 15 bit
<ul><li>— Input resistance (0 to 20 mA)</li><li>• 4 mA to 20 mA</li></ul>	100 $\Omega$ ; + approx. 0.7 V diode forward voltage Yes; 15 bit
— Input resistance (4 mA to 20 mA)  Cable length	100 Ω; + approx. 0.7 V diode forward voltage
• shielded, max.	1 000 m; 200 m for voltage measurement
Analog value generation for the inputs	1 000 III, 200 III Ioi Voltage measurement
	intermeting (Cinner Delta)
Measurement principle Integration and conversion time/resolution per channel	integrating (Sigma-Delta)
	16 bit
Resolution with overrange (bit including sign), max.	Yes
<ul> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference</li> </ul>	16.6 / 50 / 60 Hz
frequency f1 in Hz	10.0 / 30 / 00 HZ
Conversion time (per channel)	180 / 60 / 50 ms
Smoothing of measured values	
Smoothing of measured values  • Number of smoothing levels	4; None; 4/8/16 times
<ul><li>Smoothing of measured values</li><li>Number of smoothing levels</li><li>parameterizable</li></ul>	
Number of smoothing levels	4; None; 4/8/16 times
<ul><li>Number of smoothing levels</li><li>parameterizable</li><li>Encoder</li></ul>	4; None; 4/8/16 times
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> </ul>	4; None; 4/8/16 times Yes
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> </ul>	4; None; 4/8/16 times
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> </ul>	4; None; 4/8/16 times Yes  Yes  Yes
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> </ul>	4; None; 4/8/16 times Yes
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul>	4; None; 4/8/16 times Yes  Yes  Yes  Yes 650 $\Omega$
Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies	4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No
Number of smoothing levels parameterizable  Encoder  Connection of signal encoders  for voltage measurement for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)	4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 %
Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-)	4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K
Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min.	4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K 50 dB
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer         <ul> <li>Burden of 2-wire transmitter, max.</li> </ul> </li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input</li> </ul>	4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K
Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K 50 dB
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer         <ul> <li>Burden of 2-wire transmitter, max.</li> </ul> </li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input</li> </ul>	4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K 50 dB
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer         <ul> <li>Burden of 2-wire transmitter, max.</li> </ul> </li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Voltage, relative to input range, (+/-)</li> </ul>	4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer         <ul> <li>Burden of 2-wire transmitter, max.</li> </ul> </li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> </ul>	4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %  0.5 %
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer         <ul> <li>Burden of 2-wire transmitter, max.</li> </ul> </li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Voltage, relative to input range, (+/-)</li> </ul>	4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %  0.5 %
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer         <ul> <li>Burden of 2-wire transmitter, max.</li> </ul> </li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> </ul>	4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %  0.5 % 0.5 %
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer         <ul> <li>Burden of 2-wire transmitter, max.</li> </ul> </li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Voltage, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Voltage, relative to input range, (+/-)</li> </ul>	4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %  0.5 %  0.5 %  0.3 % 0.3 % 0.3 %
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer  — Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Series mode interference (peak value of</li> </ul>	4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %  0.5 %  0.5 %  0.3 % 0.3 % 0.3 %
<ul> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer         <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies         <ul> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> </ul> </li> <li>Operational error limit in overall temperature range         <ul> <li>Voltage, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 =</li> </ul> </li> </ul>	4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %  0.5 %  0.5 %  0.3 % 0.3 % interference frequency

Common mode interference, min.	90 dB
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Alarms	
Diagnostic alarm	Yes
Limit value alarm	No
Diagnoses	
Monitoring the supply voltage	Yes
Wire-break	Yes; at 4 to 20 mA
Short-circuit	Yes; with 1 to 5 V or 2-wire mode: Short-circuit of the encoder supply to ground or of an input to the encoder supply
Group error	Yes
Overflow/underflow	Yes
Diagnostics indication LED	
<ul> <li>Monitoring of the supply voltage (PWR-LED)</li> </ul>	Yes; green LED
<ul> <li>Channel status display</li> </ul>	Yes; green LED
<ul> <li>for channel diagnostics</li> </ul>	No
<ul> <li>for module diagnostics</li> </ul>	Yes; green/red LED
Potential separation	
Potential separation channels	
• between the channels	Yes; channel group-specific between 2-wire current input group and voltage input group
<ul> <li>between the channels and backplane bus</li> </ul>	Yes
<ul> <li>between the channels and the power supply of the electronics</li> </ul>	Yes; only for voltage inputs
Permissible potential difference	
between the inputs (UCM)	10 V DC
Isolation	
Isolation tested with	707 V DC (type test)
Standards, approvals, certificates	
Suitable for applications according to AMS 2750	Yes; Declaration of Conformity, see online support entry 109757262
Suitable for applications according to CQI-9	Yes
Ambient conditions	
Ambient temperature during operation	
• horizontal installation, min.	-30 °C; < 0 °C as of FS02
horizontal installation, max.	60 °C
vertical installation, min.	-30 °C; < 0 °C as of FS02
vertical installation, max.	50 °C
Altitude during operation relating to sea level	
Installation altitude above sea level, max.	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	2 222 m, 100 multida
Width	15 mm
Height	73 mm
Depth	75 mm
Weights	00 11111
	24 ~
Weight, approx.	31 g
last modified:	2/6/2021 🖸