SIEMENS

Data sheet

6ES7155-6AU01-0BN0



SIMATIC ET 200SP, PROFINET interface module IM 155-6PN Standard, max. 32 I/O modules, and 16 ET 200AL modules, single hot swap, incl. server module (6ES7193-6PA00-0AA0)

General information	
Product type designation	IM 155-6 PN ST
HW functional status	From FS03
Firmware version	
 FW update possible 	Yes
Product function	
 I&M data 	Yes; I&M0 to I&M3
 Module swapping during operation (hot swapping) 	Yes; Single hot swapping
 Isochronous mode 	No
Engineering with	
 STEP 7 TIA Portal configurable/integrated from version 	V14
 STEP 7 configurable/integrated from version 	V5.5 SP4 and higher
 PROFINET from GSD version/GSD revision 	V2.3 / -
Configuration control	
via dataset	Yes
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Short-circuit protection	Yes
Mains buffering	
 Mains/voltage failure stored energy time 	10 ms
Input current	
Current consumption (rated value)	450 mA
Current consumption, max.	550 mA
Inrush current, max.	3.7 A
l²t	0.09 A ² ·s
Power	
Infeed power to the backplane bus	4.5 W
Power loss	
Power loss, typ.	1.9 W
Address area	
Address space per module	
 Address space per module, max. 	256 byte; per input / output
Address space per station	
Address space per station, max.	512 byte; Dependent on configuration
Hardware configuration	
Rack	

 Quantity of operable ET 200SP modules, max. 	32
Quantity of operable ET 200AL modules, max.	16
Submodules	
 Number of submodules per station, max. 	256
Interfaces	
Number of PROFINET interfaces	1; 2 ports (switch)
1. Interface	
Interface types	
Number of ports	2
integrated switch	Yes
BusAdapter (PROFINET)	Yes; compatible BusAdapters: BA 2x RJ45, BA 2x FC, BA 2x M12
Protocols	
PROFINET IO Device	Yes
Open IE communication	Yes
Media redundancy	Yes; PROFINET MRP
PROFINET IO Device	
Services	
— IRT	Vac: with cond evalue of between 250 up and 4 ms in increments of 125
— IR1	Yes; with send cycles of between 250 μs and 4 ms in increments of 125 μs
— PROFlenergy	Yes
— Prioritized startup	Yes
— Shared device	Yes
 — Number of IO Controllers with shared device, max. 	2
Interface types	
RJ 45 (Ethernet)	
 Transmission procedure 	PROFINET with 100 Mbit/s full duplex (100BASE-TX)
• 100 Mbps	Yes; PROFINET with 100 Mbit/s full duplex (100BASE-TX)
 Autonegotiation 	Yes
 Autocrossing 	Yes
Protocols	
PROFINET IO Device	
Services	
0011000	
— IRT	Yes; with send cycles of between 250 µs and 4 ms in increments of 125
	Yes; with send cycles of between 250 μs and 4 ms in increments of 125 μs
— IRT	μs
— IRT — PROFlenergy	µs Yes
— IRT — PROFlenergy — Prioritized startup	μs Yes Yes
— IRT — PROFlenergy — Prioritized startup — Shared device	μs Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, 	μs Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. 	μs Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode 	μs Yes Yes 2
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) 	μs Yes Yes 2
 – IRT – PROFlenergy – Prioritized startup – Shared device – Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy 	μs Yes Yes 2 No
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP 	μs Yes Yes 2 No Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD 	μs Yes Yes 2 No Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication 	μs Yes Yes 2 No Yes No Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP 	μs Yes Yes 2 No Yes No
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP 	μs Yes Yes 2 No Yes No
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information 	μs Yes Yes 2 No Yes No Yes Yes Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator 	μs Yes Yes 2 No Yes No Yes Yes Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator Alarms 	μs Yes Yes 2 No Yes No Yes Yes Yes Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator Alarms Diagnostics function 	μs Yes Yes 2 No Yes No Yes Yes Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator Alarms Diagnostics function LED 	μs Yes Yes Yes 2 No Yes No Yes Yes Yes Yes Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator Alarms Diagnostics function RUN LED 	μs Yes Yes Yes No Yes No Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator Alarms Diagnostics function RUN LED ERROR LED 	μs Yes Yes Yes 2 No Yes No Yes Yes Yes Yes Yes Yes Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator Alarms Diagnostics function ERROR LED MAINT LED 	μs Yes Yes 2 No Yes No Yes Yes Yes Yes Yes Yes Yes Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator Alarms Diagnostics function ERROR LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) 	μs Yes Yes 2 2 No Yes No Yes Yes Yes Yes Yes Yes Yes Yes Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator Alarms Diagnostics function ERROR LED MAINT LED 	μs Yes Yes 2 No Yes No Yes Yes Yes Yes Yes Yes Yes Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator Alarms Diagnostics function ERROR LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) 	μs Yes Yes 2 2 No Yes No Yes Yes Yes Yes Yes Yes Yes Yes Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator Alarms Diagnostics function ERROR LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Connection display LINK TX/RX 	μs Yes Yes 2 2 No Yes No Yes Yes Yes Yes Yes Yes Yes Yes Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator Alarms Diagnostics function ERROR LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Connection display LINK TX/RX 	μs Yes Yes 2 No No Yes No Yes Yes Yes Yes Yes Yes Yes Yes Yes Yes
 IRT PROFlenergy Prioritized startup Shared device Number of IO Controllers with shared device, max. Redundancy mode PROFINET system redundancy (S2) Media redundancy MRP MRP MRPD Open IE communication TCP/IP SNMP LLDP Interrupts/diagnostics/status information Status indicator Alarms Diagnostics function ERROR LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Connection display LINK TX/RX 	μs Yes Yes 2 No Yes No Yes Yes Yes Yes Yes Yes Yes Yes Yes Yes

Permissible potential difference	
between different circuits	Safety extra low voltage SELV
Isolation	
Isolation tested with	707 V DC (type test)
Standards, approvals, certificates	
Network loading class	2
Security level	According to Security Level 1 Test Cases V1.1.1
Ambient conditions	
Ambient temperature during operation	
 horizontal installation, min. 	-30 °C
 horizontal installation, max. 	60 °C
 vertical installation, min. 	-30 °C
 vertical installation, max. 	50 °C
Altitude during operation relating to sea level	
 Installation altitude above sea level, max. 	5 000 m
connection method / header	
ET-Connection	
 via BU/BA Send 	Yes; + 16 ET 200AL modules
Dimensions	
Width	50 mm
Height	117 mm
Depth	74 mm
Weights	
Weight, approx.	147 g; without BusAdapter
last modified:	2/21/2022

last modified:

3/31/2023 🖸