6ES7313-5BG04-0AB0

Data sheet



SIMATIC S7-300, CPU 313C, Compact CPU with MPI, 24 DI/16 DO, 4 AI, 2 AO, 1 Pt100, 3 high-speed counters (30 kHz), Integr. power supply 24 V DC, work memory 128 KB, Front connector (2x 40-pole) and Micro Memory Card required

General information	
HW functional status	01
Firmware version	V3.3
Engineering with	
Programming package	STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
external protection for power supply lines (recommendation)	Miniature circuit breaker, type C; min. 2 A; miniature circuit breaker type B, min. 4 A
Mains buffering	
 Mains/voltage failure stored energy time 	5 ms
Repeat rate, min.	1 s
Load voltage L+	
Digital inputs	
— load voltage / at digital input / at DC / rated value	24 V
— Reverse polarity protection	Yes
Digital outputs	
— Rated value (DC)	24 V
— Reverse polarity protection	No
Input current	
Current consumption (rated value)	650 mA
Current consumption (in no-load operation), typ.	150 mA
Inrush current, typ.	5 A
l²t	0.7 A²-s
Digital inputs	
• from load voltage L+ (without load), max.	80 mA
Digital outputs	
• from load voltage L+, max.	50 mA
Power loss	
Power loss, typ.	12 W
Memory	
Work memory	
• integrated	128 kbyte
expandable	No
Load memory	
• Plug-in (MMC)	Yes
• Plug-in (MMC), max.	8 Mbyte
 Data management on MMC (after last programming), min. 	10 a

Backup	
• present	Yes; Guaranteed by MMC (maintenance-free)
without battery	Yes; Program and data
CPU processing times	. oo, og.a and add
for bit operations, typ.	0.07 μs
for word operations, typ.	0.15 µs
for fixed point arithmetic, typ.	0.2 μs
for floating point arithmetic, typ.	0.72 μs
CPU-blocks	0.72 μ3
Number of blocks (total)	1 024; (DBs, FCs, FBs); the maximum number of loadable blocks can be
Trainibol of blocks (total)	reduced by the MMC used.
DB	
Number, max.	1 024; Number range: 1 to 16000
• Size, max.	64 kbyte
FB	
Number, max.	1 024; Number range: 0 to 7999
• Size, max.	64 kbyte
FC	
• Number, max.	1 024; Number range: 0 to 7999
• Size, max.	64 kbyte
OB	
Number, max.	see instruction list
• Size, max.	64 kbyte
Number of free cycle OBs	1; OB 1
Number of time alarm OBs	1; OB 10
Number of delay alarm OBs	2; OB 20, 21
Number of cyclic interrupt OBs	4; OB 32, 33, 34, 35
Number of process alarm OBs	1; OB 40
Number of startup OBs	1; OB 100
Number of asynchronous error OBs	4; OB 80, 82, 85, 87
Number of synchronous error OBs	2; OB 121, 122
Nesting depth	
per priority class	16
additional within an error OB	4
Counters, timers and their retentivity	
S7 counter	050
Number Patenti ita	256
Retentivity	Vee
— adjustable	Yes
— preset Counting range	Z 0 to Z 7
— counting range / of S7 counters / initial value	0
— counting range / of S7 counters / initial value — counting range / of S7 counters / full-scale value	999
EC counter	
• present	Yes
• Type	SFB
• Number	Unlimited (limited only by RAM capacity)
S7 times	Chamber (miniod only by to the outputity)
• Number	256
Retentivity	
— adjustable	Yes
— aujustable	
•	No retentivity
— preset	No retentivity
— preset Time range	No retentivity 10 ms
— preset Time range — time range / of the S7 timers / initial value	10 ms
preset Time range time range / of the S7 timers / initial value time range / of the S7 timers / full-scale value	
— preset Time range — time range / of the S7 timers / initial value — time range / of the S7 timers / full-scale value IEC timer	10 ms 9 990 s
— preset Time range — time range / of the S7 timers / initial value — time range / of the S7 timers / full-scale value IEC timer • present	10 ms 9 990 s Yes
— preset Time range — time range / of the S7 timers / initial value — time range / of the S7 timers / full-scale value IEC timer	10 ms 9 990 s Yes SFB
— preset Time range — time range / of the S7 timers / initial value — time range / of the S7 timers / full-scale value IEC timer • present • Type	10 ms 9 990 s Yes

Elea	
Flag ◆ Size, max.	256 byte
Retentivity available	Yes; MB 0 to MB 255
Retentivity available Retentivity preset	MB 0 to MB 15
Number of clock memories	8; 1 memory byte
Data blocks	o, i memory byte
	Voca via non ratain proporty on DD
Retentivity adjustable Detentivity assest	Yes; via non-retain property on DB
Retentivity preset	Yes
Local data	20 librates May 2040 by too you block
per priority class, max. Address area	32 kbyte; Max. 2048 bytes per block
I/O address area	1.004 byto
• Inputs	1 024 byte
Outputs of which distributed	1 024 byte
— Inputs	none
— Outputs	none
Process image	1.024 byto
• Inputs	1 024 byte
Outputs Inputs adjustable	1 024 byte
Inputs, adjustable Outputs, adjustable	1 024 byte
Outputs, adjustable Inputs, default	1 024 byte
Inputs, default	128 byte
Outputs, default Pefault addresses of the integrated channels.	128 byte
Default addresses of the integrated channels	104.0 to 100.7
— Digital inputs	124.0 to 126.7
— Digital outputs	124.0 to 125.7
— Analog inputs	752 to 761
— Analog outputs	752 to 755
Digital channels	4.040
• Inputs	1 016
— of which central	1 016
Outputs	1 008
— of which central	1 008
Analog channels	050
• Inputs	253
— of which central	253
Outputs	250
— of which central	250
Hardware configuration	
Number of expansion units, max.	3
Number of DP masters	
• integrated	none
• via CP	4
Number of operable FMs and CPs (recommended)	
• FM	8
• CP, PtP	8
• CP, LAN	6
Rack	
• Racks, max.	4
Modules per rack, max.	8; In rack 3 max. 7
Time of day	
Clock	
Hardware clock (real-time)	Yes
 retentive and synchronizable 	Yes
Backup time	6 wk; At 40 °C ambient temperature
 Deviation per day, max. 	10 s; Typ.: 2 s
 Behavior of the clock following POWER-ON 	Clock continues running after POWER OFF
Behavior of the clock following expiry of backup period	the clock continues at the time of day it had when power was switched off
Operating hours counter	

1
0
0 to 2^31 hours (when using SFC 101)
1 h
Yes; Must be restarted at each restart
Yes
Yes
Yes
Yes
No
24
12
24
Yes
24
12
12
24 V
-3 to +5V
+15 to +30 V
8 mA
Yes; $0.1/0.3/3/15$ ms (You can reconfigure the input delay of the standard inputs during program runtime. Please note that under certain circumstances your newly set filter time may not be effective until the next filter cycle.)
3 ms
16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency
1 000 m; 100 m for technological functions
600 m; for technological functions: No
100 m; at maximum count frequency
not allowed
16
4; Notice: You cannot connect the fast outputs of your CPU in parallel
16
Yes; Clocked electronically
1 A
L+ (-48 V)
Yes
5 W
48 Ω
4 kΩ
L+ (-0.8 V)
L+ (-0.8 V)
L+ (-0.8 V) 500 mA

• for signal "1" permissible range, max.	0.6 A
for signal "1" minimum load current	5 mA
for signal "0" residual current, max.	0.5 mA
Parallel switching of two outputs	
• for uprating	No Was
for redundant control of a load Outtobic of forward and a load	Yes
Switching frequency	400 H-
with resistive load, max.	100 Hz 0.5 Hz
with inductive load, max. an lower load, max.	100 Hz
on lamp load, max.of the pulse outputs, with resistive load, max.	2.5 kHz
Total current of the outputs (per group)	2.3 KHZ
horizontal installation	
— up to 40 °C, max.	3 A
— up to 60 °C, max.	2 A
vertical installation	
— up to 40 °C, max.	2 A
Cable length	
• shielded, max.	1 000 m
unshielded, max.	600 m
Analog inputs	
Number of analog inputs	4
For voltage/current measurement	4
For resistance/resistance thermometer measurement	1
integrated channels (AI)	5; 4x current/voltage, 1x resistance
permissible input voltage for current input (destruction limit), max.	5 V; Permanent
permissible input voltage for voltage input (destruction limit), max.	30 V; Permanent
permissible input current for voltage input (destruction limit), max.	0.5 mA; Permanent
permissible input current for current input (destruction limit), max.	50 mA; Permanent
Electrical input frequency, max.	400 Hz
No-load voltage for resistance-type transmitter, typ.	3.3 V
Constant measurement current for resistance-type transmitter, typ.	1.25 mA
Technical unit for temperature measurement adjustable	Yes; Degrees Celsius / degrees Fahrenheit / Kelvin
Input ranges	
 Voltage 	Yes; ± 10 V / 100 k Ω ; 0 V to 10 V / 100 k Ω
Current	Yes; ±20 mA / 100 Ω ; 0 mA to 20 mA / 100 Ω ; 4 mA to 20 mA / 100 Ω
Resistance thermometer	Yes; Pt 100 / 10 MΩ
Resistance	Yes; 0 Ω to 600 Ω / 10 M Ω
Input ranges (rated values), voltages	
• 0 to +10 V	Yes
— Input resistance (0 to 10 V)	100 kΩ
Input ranges (rated values), currents	
• 0 to 20 mA	Yes
— Input resistance (0 to 20 mA)	100 Ω
• -20 mA to +20 mA	Yes
— Input resistance (-20 mA to +20 mA)	100 Ω
• 4 mA to 20 mA	Yes
— Input resistance (4 mA to 20 mA)	100 Ω
Input ranges (rated values), resistance thermometer	V
• Pt 100	Yes
— Input resistance (Pt 100)	10 ΜΩ
Input ranges (rated values), resistors	Voc
• 0 to 600 ohms	Yes
— Input resistance (0 to 600 ohms)	10 ΜΩ
Thermocouple (TC)	
Temperature compensation	No
— parameterizable	INU

Characteristic linearization	
parameterizable	Yes; by software
— for resistance thermometer	Pt 100
Cable length	
• shielded, max.	100 m
Analog outputs	
Number of analog outputs	2
integrated channels (AO)	2
Voltage output, short-circuit protection	Yes
Voltage output, short-circuit current, max.	55 mA
Current output, no-load voltage, max.	14 V
Output ranges, voltage	
• 0 to 10 V	Yes
• -10 V to +10 V	Yes
Output ranges, current	
• 0 to 20 mA	Yes
• -20 mA to +20 mA	Yes
• 4 mA to 20 mA	Yes
Connection of actuators	
for voltage output two-wire connection	Yes; Without compensation of the line resistances
for voltage output four-wire connection	No
for current output two-wire connection	Yes
Load impedance (in rated range of output)	
with voltage outputs, min.	1 kΩ
with voltage outputs, min. with voltage outputs, capacitive load, max.	0.1 μF
 with voltage outputs, capacitive load, max. with current outputs, max. 	300 Ω
-	
with current outputs, inductive load, max. Posturation limits against externally applied voltages and surrents.	0.1 mH
Destruction limits against externally applied voltages and currents	40.V. Damanant
Voltages at the outputs towards MANA	16 V; Permanent
Current, max.	50 mA; Permanent
Cable length	
-	000
• shielded, max.	200 m
shielded, max. Analog value generation for the inputs	
shielded, max. Analog value generation for the inputs conversion method / at the analog input	200 m Actual value encryption (successive approximation)
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel	Actual value encryption (successive approximation)
shielded, max. Analog value generation for the inputs conversion method / at the analog input	
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference	Actual value encryption (successive approximation) 12 bit
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels)	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released)	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max.	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel)	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for capacitive load	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms 1 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for capacitive load for inductive load	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms 1 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for capacitive load for inductive load Encoder Connection of signal encoders	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms 1 ms 0.5 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for capacitive load for inductive load Fincoder Connection of signal encoders for voltage measurement	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms 1 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for capacitive load for inductive load Encoder Connection of signal encoders	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms 1 ms 0.5 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for capacitive load for inductive load Fincoder Connection of signal encoders for voltage measurement	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms 1 ms 0.5 ms
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for capacitive load for inductive load Encoder Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms 1 ms 0.5 ms Yes Yes; with external supply
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for capacitive load for inductive load Encoder Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer for current measurement as 4-wire transducer	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms 1 ms 0.5 ms Yes Yes; with external supply Yes
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms 1 ms 0.5 ms Yes Yes; with external supply Yes Yes; Without compensation of the line resistances
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for apacitive load for inductive load Encoder Connection of signal encoders for ourrent measurement for current measurement as 2-wire transducer for current measurement with two-wire connection for resistance measurement with three-wire connection	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms 1 ms 0.5 ms Yes Yes; with external supply Yes Yes; Without compensation of the line resistances No
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for capacitive load for inductive load Fincoder Connection of signal encoders for outrent measurement for current measurement as 2-wire transducer for current measurement as 4-wire transducer for resistance measurement with two-wire connection for resistance measurement with three-wire connection for resistance measurement with four-wire connection	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms 1 ms 0.5 ms Yes Yes; with external supply Yes Yes; Without compensation of the line resistances No
shielded, max. Analog value generation for the inputs conversion method / at the analog input Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Time constant of the input filter Basic execution time of the module (all channels released) Analog value generation for the outputs Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Conversion time (per channel) Settling time for resistive load for capacitive load for inductive load Encoder Connection of signal encoders for ourrent measurement for current measurement as 2-wire transducer for resistance measurement with two-wire connection for resistance measurement with three-wire connection for resistance measurement with four-wire connection for resistance measurement with four-wire connection	Actual value encryption (successive approximation) 12 bit Yes; 16.6 / 20 ms 50 / 60 Hz 0.38 ms 1 ms 12 bit 1 ms 0.6 ms 1 ms 0.5 ms Yes Yes; with external supply Yes Yes; Without compensation of the line resistances No No

Errors/accuracies	
Temperature error (relative to input range), (+/-)	0.006 %/K
Crosstalk between the inputs, min.	60 dB
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	0.06 %
Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-)	0.1 %
Linearity error (relative to output range), (+/-)	0.15 %
Temperature error (relative to output range), (+/-)	0.01 %/K
Crosstalk between the outputs, min.	60 dB
Repeat accuracy in steady state at 25 °C (relative to output range), (+/-)	0.06 %
Operational error limit in overall temperature range	
 Voltage, relative to input range, (+/-) 	1 %
 Current, relative to input range, (+/-) 	1 %
 Resistance, relative to input range, (+/-) 	1 %
 Voltage, relative to output range, (+/-) 	1 %
 Current, relative to output range, (+/-) 	1 %
Basic error limit (operational limit at 25 °C)	
Voltage, relative to input range, (+/-)	0.8 %; Linearity error ±0.06 %
• Current, relative to input range, (+/-)	0.8 %; Linearity error ±0.06 %
• Resistance, relative to input range, (+/-)	0.8 %; Linearity error ±0.2 %
Resistance thermometer, relative to input range, (+/-)	0.8 %
Voltage, relative to output range, (+/-)	0.8 %
Current, relative to output range, (+/-)	0.8 %
Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference	erence frequency
Series mode interference (peak value of interference < rated value of input range), min.	30 dB
• Common mode interference, min.	40 dB
Interfaces	
Number of industrial Ethernet interfaces	0
Number of PROFINET interfaces	0
Number of RS 485 interfaces	1; MPI
Number of RS 422 interfaces	0
1. Interface	
Interface type	Integrated RS 485 interface
Isolated	No
Interface types	
• RS 485	Yes
Output current of the interface, max.	200 mA
Protocols	
• MPI	Yes
PROFIBUS DP master	No
PROFIBUS DP slave	No
Point-to-point connection	No
MPI	
Transmission rate, max.	187.5 kbit/s
Services	
— PG/OP communication	Yes
— Routing	No
Global data communication	Yes
S7 basic communication	Yes
— S7 communication	Yes; Only server, configured on one side
— S7 communication, as client	No; but via CP and loadable FB
— S7 communication, as server	Yes
Protocols	
	No
PROFIsafe	No
communication functions / header	Voc
PG/OP communication	Yes
Data record routing	No
Global data communication	
supported	Yes

 Number of GD loops, max. 	8
 Number of GD packets, max. 	8
 Number of GD packets, transmitter, max. 	8
 Number of GD packets, receiver, max. 	8
 Size of GD packets, max. 	22 byte
 Size of GD packet (of which consistent), max. 	22 byte
S7 basic communication	
communication function / S7 basic communication	Yes
User data per job, max.	76 byte
User data per job (of which consistent), max.	76 byte; 76 bytes (with X SEND or X RCV); 64 bytes (with X PUT or X GET
	as server)
S7 communication	
• supported	Yes
as server	Yes
• as client	Yes; Via CP and loadable FB
User data per job, max.	180 byte; With PUT/GET
User data per job (of which consistent), max.	240 byte; as server
S5 compatible communication	240 byte, as server
·	Yes; via CP and loadable FC
supported Number of connections	1 65, VIA OF ANU IDAUADIE FO
Number of connections	0
• overall	8
usable for PG communication	7
 reserved for PG communication 	1
— adjustable for PG communication, min.	1
 adjustable for PG communication, max. 	7
 usable for OP communication 	7
 reserved for OP communication 	1
 adjustable for OP communication, min. 	1
 adjustable for OP communication, max. 	7
usable for S7 basic communication	4
 reserved for S7 basic communication 	0
adjustable for S7 basic communication, min.	0
adjustable for S7 basic communication, max.	4
S7 message functions	•
	O. Depending on the configured connections for DC/OD and C7 hasis
Number of login stations for message functions, max.	8; Depending on the configured connections for PG/OP and S7 basic communication
Process diagnostic messages	Yes
simultaneously active Alarm-S blocks, max.	300
Test commissioning functions	
Status block	Yes; Up to 2 simultaneously
Single step	Yes
Number of breakpoints	4
Status/control	
Status/control Status/control variable	Yes
Status/control variable Variables	Inputs, outputs, memory bits, DB, times, counters
Status/control variableVariablesNumber of variables, max.	Inputs, outputs, memory bits, DB, times, counters 30
 Status/control variable Variables Number of variables, max. of which status variables, max. 	Inputs, outputs, memory bits, DB, times, counters 30 30
 Status/control variable Variables Number of variables, max. of which status variables, max. of which control variables, max. 	Inputs, outputs, memory bits, DB, times, counters 30
Status/control variable Variables Number of variables, max. of which status variables, max. of which control variables, max. Forcing	Inputs, outputs, memory bits, DB, times, counters 30 30 14
Status/control variable Variables Number of variables, max. of which status variables, max. of which control variables, max. Forcing Forcing	Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes
Status/control variable Variables Number of variables, max. — of which status variables, max. — of which control variables, max. Forcing Forcing Forcing, variables	Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs
Status/control variable Variables Number of variables, max. — of which status variables, max. — of which control variables, max. Forcing Forcing Forcing Number of variables, max.	Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes
Status/control variable Variables Number of variables, max. of which status variables, max. of which control variables, max. Forcing Forcing Forcing Variables Number of variables, max. Diagnostic buffer	Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10
Status/control variable Variables Number of variables, max. — of which status variables, max. — of which control variables, max. Forcing Forcing Forcing Number of variables, max.	Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10
Status/control variable Variables Number of variables, max. of which status variables, max. of which control variables, max. Forcing Forcing Forcing Variables Number of variables, max. Diagnostic buffer	Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10
Status/control variable Variables Number of variables, max. of which status variables, max. of which control variables, max. Forcing Forcing Forcing Variables Number of variables, max. Diagnostic buffer present	Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10
Status/control variable Variables Number of variables, max. of which status variables, max. of which control variables, max. Forcing Forcing Forcing, variables Number of variables, max. Diagnostic buffer present Number of entries, max.	Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes 500
Status/control variable Variables Number of variables, max. — of which status variables, max. — of which control variables, max. Forcing Forcing Forcing, variables Number of variables, max. Diagnostic buffer present Number of entries, max. — adjustable	Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes 500 No
Status/control variable Variables Number of variables, max. of which status variables, max. of which control variables, max. Forcing Forcing Forcing, variables Number of variables, max. Diagnostic buffer present Number of entries, max. adjustable of which powerfail-proof	Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes 500 No 100; Only the last 100 entries are retained
Status/control variable Variables Number of variables, max. of which status variables, max. of which control variables, max. Forcing Forcing Forcing, variables Number of variables, max. Diagnostic buffer present Number of entries, max. adjustable of which powerfail-proof Number of entries readable in RUN, max.	Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes 500 No 100; Only the last 100 entries are retained 499
Status/control variable Variables Number of variables, max. — of which status variables, max. — of which control variables, max. Forcing Forcing Forcing, variables Number of variables, max. Diagnostic buffer present Number of entries, max. — adjustable — of which powerfail-proof Number of entries readable in RUN, max. — adjustable	Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes 500 No 100; Only the last 100 entries are retained 499 Yes; From 10 to 499

test-/initiation function / service data readable	Yes
Interrupts/diagnostics/status information	
Diagnostics indication LED	
Status indicator digital input (green)	Yes
Status indicator digital input (green) Status indicator digital output (green)	Yes
Integrated Functions	165
Frequency measurement	Yes
Number of frequency meters	3; up to 30 kHz (see "Technological Functions" manual)
controlled positioning	No
integrated function blocks (closed-loop control)	Yes; PID controller (see "Technological Functions" manual)
PID controller	Yes
Number of pulse outputs	3; Pulse width modulation up to 2.5 kHz (see "Technological Functions"
Number of pulse outputs	Manual)
Limit frequency (pulse)	2.5 kHz
Potential separation	
Potential separation digital inputs	
Potential separation digital inputs	Yes
between the channels	No
 between the channels and backplane bus 	Yes
Potential separation digital outputs	
Potential separation digital outputs	Yes
between the channels	Yes
 between the channels, in groups of 	8
between the channels and backplane bus	Yes
Potential separation analog inputs	
Potential separation analog inputs	Yes; common for analog I/O
 between the channels 	No
 between the channels and backplane bus 	Yes
Potential separation analog outputs	
Potential separation analog outputs	Yes; common for analog I/O
between the channels	No
 between the channels and backplane bus 	Yes
Isolation	
Isolation tested with	600 V DC
Ambient conditions	
Ambient temperature during operation	
• min.	0 °C
• max.	60 °C
configuration / header	
Configuration software	
• STEP 7	Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP
	203
STEP 7 Lite	No
configuration / programming / header	
Command set	see instruction list
 Nesting levels 	8
 System functions (SFC) 	see instruction list
System function blocks (SFB)	see instruction list
Programming language	
— LAD	Yes
— FBD	Yes
— STL	Yes
— SCL	Yes
— CFC	Yes
— GRAPH	Yes
— HiGraph®	Yes
Know-how protection	
User program protection/password protection	Yes
Block encryption	Yes; With S7 block Privacy
Dimensions	
Width	120 mm

Height	125 mm
Depth	130 mm
Weights	
Weight, approx.	660 g

last modified: 4/25/2024 🖸