

Mini Sound Level Meter

With 4 Digit LCD display



Technical Datasheet



MT95

The MT95 Mini Sound Level Meter is designed to meet the measurement requirements of noise engineering, sound quality control, health, industrial safety offices in various environments. Such as factory, school, office and traffic lines.

Features

- 4 Digit LCD display
- 0.5" Electret Condenser Microphone
- Level range 35dB to 130dB
- A & C Level Weighting
- Background noise absorber
- Auto Power Off

Accessories



Noise Diffuser

General Specifications

Function	Range
Range:	35 - 130dB
Measuring range:	LO: 35dB-80dB Med: 50dB-100dB HI: 80dB-130dB Auto: 35dB-130dB
Frequency range:	31.5HZ-8KHZ
Accuracy:	3dB (under reference condition of 94dB, 1kHz)
Frequency weighting:	A and C
Microphone:	1/2 inch electret condenser microphone
Digital display:	4 digits LCD display with a resolution: 0.1dB
Display Update:	2 times / sec
Auto power off:	Meter automatically shuts down after approx. 10 minutes of inactivity.
Power supply:	One 9V battery
Low battery indication:	The low battery signal "E" flash when battery voltage drops below 7.2V; The backlight and low battery signal "E" flash twice IE battery voltage drops below 6.5V, then auto power off.
Operation temp & humidity:	0°C-40°C, 10%RH-90%RH
Storage temp & humidity:	-10°C- +60°C, 10%RH-75%RH
Weight:	184g
Dimensions:	185mm x 54mm x 36mm



Contact Us

Branches: Johannesburg | Cape Town | Durban | Port Elizabeth | Bloemfontein
 011 872 5500 | 021 556 3091 | 031 569 1024 | 041 452 1172 | 051 430 4958
 email: sales@major-tech.com | www.major-tech.com

