



INSTRUCTION MANUAL
MT600
POCKET DIGITAL THERMOMETER



Specification:

Temperature Range	-50°C to 200°C (-58°F to 392°F)
Accuracy	±2°C (±4°F)
Resolution	0.1°C
Measurement Rate	1 time per second
Auto Power Off	10 minutes
Hi/Low Temperature Alarm	Yes
Low Battery Indication	Yes
Alarm Temperature Range	-40°C to 200°C (-40°F to +392°F)
Shut down the alarm by pressing any button	Yes

Button Indication:

[AL UP] : HI/Low Temperature Alarm Switch

[HI SET] : High Temperature Alarm Setting

[LO SET] : Low Temperature Alarm Setting

[MAX/MIN] : Max/Min Reading

Operation:

1. Under normal temperature status, press the [HI SET] button to access the High Temperature Setting Interface with the “HT” symbol. Press [AL UP] button to turn the alarm function on/off. Hold the [HI SET] button for 2 seconds to access the high temperature setting with a flicker. Press [AL UP] button to turn up the value of integral quantities. Press [HI SET] button to complete and confirm the setting.
2. To set the Low Alarm, simply press the [LOW SET] button, and follow the same procedure as that of the Hi Alarm.
3. Alarm Temperature Range: -40°C to 200°C.



MAJOR TECH (PTY) LTD

South Africa

🌐 www.major-tech.com

✉ sales@major-tech.com

Australia

🌐 www.majortech.com.au

✉ info@majortech.com.au

