

Specifications:

- 1.CPU Electronic coin acceptor ,Drop Inserting Type.
- 2 Capable for accepting all worldwide Coins and Tokens.
- 3:Select coin by Diameter, Thickness and Metal Content.
- 4:CPU anti-string programs presetting against fraud.
- 5:Adjustable VR tuning for sensitivity of coin acceptance.
- 6: Allow to connect to Counter(Meter).

Voltage : DC+12V

Coin Diameter : 22mm~28mm

Coin thickness : 1.7mm~2.2mm

USER GUIDE:

1. Replace yellow plastic token to the correct coin as wish to accept in sampling clamp.
2. Adjust entry slot opening to your coin size by loosening screw on the back of metal panel for blocking bigger invalid coin from inserting.
3. Turn the screw on front lid in clockwise direction for ditching "thinner coin" through the slot of lid if necessary.
4. switch to Normal Open (N.O.) or Normal close (N.C) for signal output of coin validation upon Host requested .
5. 3 triggering TIMER SWITCH of Pulse Duration ,
 - Long duration of Pulse :. 100ms
 - Common duration of Pulse : 50ms
 - Short duration of Pulse :30ms
6. VR tuning for tolerance of coin acceptance , turn clockwise for slack and anti-clockwise for precise acceptance.
7. Shift sensitivity switch of coin acceptance downward to "special" to extend the range of discriminated ratio for twin metal coins or the coins in big tolerance.

Applications:

- Wireless PC peripherals
- Coin kiosk
- Car washing machine
- TV
- Massage chair
- Cloth dryer
- Cyber coffee
- Laundromat
- Laundry
- Computer
- Amusement machine
- Arcade machine