

Wall detector scanner WD-01 & WD-02

Introduction

The WD-01&WD-02 are wall detector to solve various problems encountered by users in decoration and drilling. It can detect metals for steel bars, copper pipes hidden in multiple scenes such as walls, ceilings, gypsum boards and cables ets..

- 3 modes for Magnetic/AC Cable/Wood/Metal
- Creative design circular hole positioning
- languages: Russian/English/Portuguese/Japanese/Chinese



Application

FNIRSI | WD-02
Wall Detector Scanner

WALL DETECTOR SCANNER



AC



WOOD



METAL



ULTRA-DEEP DETECTION
DETECTS UP TO 120MM



Technical Specifications

Detection object	Electromagnetic/AC Cable/Wood/Metal	
Ferrous metals	120mm Max	
Non-ferrous metals	100mm Max	
AC Cable	50mm Max (220V/@50Hz; 110V/60Hz)	
Single-core copper wire	40mm Max ((≥4 square millimeters))	
Wooden block	20mm Exact Mode /38mm Deep Mode	
Indication mode	Distance percentage, Light, Beeping freq.,	
Work temperature	-10~50°C	
Unit conversion	/	mm/inch
Sensitivity	/	Low/Medium/High 3 options
Display	Electronic ink display	TFT HD color screen
Languages	English/Chinese	English/Russian/Japanese/Portuguese/Chinese

Technical Specifications

	WD-01	WD-02
Battery	3.7V/300mAh lithium battery, standby time 2 hours	
Product net weight	123g	
Product size	138*68*22mm	
Standard carton	51*42*25.5cm	
Carton gross weight	14kg	
Quantity per carton	50PCS	