

# 200A AC Open Jaw Clamp Meter True RMS



## Technical Datasheet

### MT715

The MT715 True RMS 6000 count open jaw clamp meter offers a Data hold, MAX/Min function, Low impedance. The meter features a negative display screen with a illuminated rotary selector switch for use in dimly lit areas.



### Features

- Measures AC Current up to 200A
- Measures AC/DC Voltage up to 1000V
- Non-Contact Voltage
- 6000 Count LCD Display
- Resistance 60M $\Omega$
- Capacitance to 4000 $\mu$ F
- 16 mm Clamp Jaw Opening
- Backlight & Flashlight



**TRUERMS**

### Specifications

FUNCTION	RANGE
AC Current	200A
DC Voltage	1000V
AC TRMS Voltage	1000V
Resistance	60M $\Omega$
Capacitance	4000 $\mu$ F
Diode Test	1.5mA Typical
NCV Detection	Above 80V AC
Batteries	2 x 1.5V AA Batteries
Jaw Size	16mm
Dimensions	230 x 44 x 66mm
Weight	259g



Meter includes flash light to light up area of test



Red Light indicates detection of Non Contact Voltage (NCV)



6000 Count Negative LCD Display



Rear entry of standard 4mm Test Lead Terminals



16mm Open Jaw Conductor Size



Convenient built-in test lead storage



Two hand operation safely allows reading on display when measuring



Range markings are backlit for use in dimly lit areas

### Contact Us

Branches: Johannesburg | Cape Town | Durban | Port Elizabeth | Bloemfontein  
 011 872 5500 | 021 556 3091 | 031 569 1024 | 041 452 1172 | 051 430 4958  
 email: sales@major-tech.com | www.major-tech.com

