## 600V AC/DC Multimeter True RMS



# **Technical Datasheet**





#### Features:

- 2000 Count Digital Display
- 10A AC/DC
- 600V AC/DC
- 2MΩ Resistance
- Battery Test Current: 9V & 1.5V

#### **MT874**

The MT874 is a durable and attractive compact True RMS Multimeter with a high contrast LCD display with detailed display icons. Equipped with 7 measurement functions and 20 ranges, each test position is quickly and easily selected with a simple turn of the selector switch. The meter has a double moulded housing and has an IEC 61010-1 CAT III 600V safety rating. The sturdy structure is designed to withstand the rugged environment of a work site and has been drop tested up to 2 meters. There is a built-in tilt stand for hands free convenience as well as low battery indication and auto power off. This meter is suitable for commercial electricians, electronics technicians and DIY users.

### **Specifications:**

FUNCTION	FUNCTION	RANGE		
DC Current	Range	200mA - 10A		
	Resolution	0.1mA - 0.01/	0.1mA - 0.01A	
	Accuracy	±(2.0% + 5 Digits)		
AC True RMS Current	Range	200mA - 10A		
	Resolution	0.1mA - 0.01A		
	Accuracy	±(2.0% + 5 Digits)		
DC Voltage	Range	200mV - 600V		
	Resolution	0.1mV - 1V		
	Accuracy	±(0.5% + 5 Digits)		
AC True RMS Voltage	Range	200V - 600V		
	Resolution	0.1V - 1V		
	Accuracy	±(1.2% + 10 Digits)		
Resistance	Range	200Ω - 2ΜΩ		
	Resolution	0.1Ω - 0.001ΜΩ		
	Accuracy	±(0.8% + 5 Digits)		
Battery Test	Voltage	9V	1.5V	
	Resolution	0.01V	0.001V	
	Accuracy	±(1.0% + 5 D	igits)	
Continuity	Buzzer sounds at approx. $50\Omega$			
Diode	Current 1mA, Voltage 3V DC			
Data Hold	Yes			
Dimensions	154 x 74 x 43mm			
Weight	255g			
Batteries	2 x AAA			
Accessories	Test Leads			

Contact Us Johannesburg 011 872 5500

Cape Town Durb 021 556 3091 031 () www.major-tech.com

Durban 031 569 1024

Port Elizabeth1024041 452 1172➤ sales@major-tech.com

Bloemfontein 051 430 4958